



SHANGHAI PING YIAO TRADING CO.,LTD.

Tel: 86-21-64705533

Fax: 86-21-64820538

24H: 86-15900706965

Website: www.pingyiao.com

E-mail: info@pingyiao.com

**Waterbased, foam free, strong,
high-performance cleaner**

Non-combustible, unscented, phosphate-free, corrosion preventing

RIVOLTA B.R.X. 624 removes all kinds of grease, oil and other resistant contaminations from metal, plastic, ceramics and other surfaces.

RIVOLTA B.R.X. 624 is used by the industry, craftman's shops, workshops, power plants, fleets, purification plants, steel mills, motor vehicle pools and other public areas.

RIVOLTA B.R.X. 624 is very economic since dilutable with up to 50 parts of water. The ratio of mixture for the use of B.R.X. 624 depends on the type and grade of contamination and the cleaning-procedure. By heating up the product up to 80°C the cleaning effect will be increased noticeable.

RIVOLTA B.R.X. 624 can be used for many cleaning-procedures like automatic-spray-washing-machines, immersion, brushing, sprinkling and in ultrasonic installations.

Colour: colourless

Odour: odourless

Technical data	Unit of measurement	Norm	B.R.X. 624
Density (20 °C)	g/ml	DIN 51757	1.12
pH value (1% solution)	-	-	11.3

Material-attack: RIVOLTA B.R.X. 624 is not aggressive to common paints, plastics and rubber.
B.R.X. 624 is not suitable for aluminium, zinc and zinc-coated surfaces.

Examples of mixture ratios:

automatic-spray-washing-machines:	1:10 - 1:50
degreasing of metal, handwashing:	1:10 - 1:30
degreasing of metal, immersion:	1:20 - 1:50
ultrasonic application:	1:10 - 1:30

RIVOLTA B.R.X. 624 contains corrosion-inhibitors. Shiny metal parts are short-term protected against corrosion or rust film. For a long-term conservation we recommend a treatment with our corrosion inhibiting products of the RIVOLTA K.S.P.-line.

This text contains facts and statements and is determined with our best knowledge and will be checked continuously. These statements are depending - among other reasons - on experiences gained in the industry. We only pass them on without liability. Before using our products you should test the applicability and you should convince yourself about the satisfactory performance. Our application examples and suggestions should not request to violate patent rights